

Instructional Audio Components



Flexmike...

Flexmike is designed for the teacher: easy to operate and comfortable to wear.

Volume controls allow the teacher to quickly and conveniently make adjustments to the microphone volume as needed.

Description	Pendant-style transceiver
Earbud lanyard	Magnetic clasp with integrated earbud
Wireless communication	Access Technology (1.9 GHz)
Audio distortion	<1%
Integrated microphone	Uni-directional electret
Earbud output	3.5mm
Digital audio interface	USB-C 2-way digital audio interface
Volume control	+/- 6 dB
Battery power	3.7V Lithium polymer battery pack
Battery life	8 hours (fully charged)
Charging	2 contacts for cradle charging
USB connection	Type C for charging and audio
Power	On/off switch
Pairing	IR emitter to enable one-button pairing with amplifier
Dimensions (L x W x H)	2.9" x 1.1" x 0.7" (74 x 28 x 18mm)
Weight	1.2 oz (34g)



Sharemike...

Sharemike is designed for student pass-around use so that all students can clearly be heard in the classroom.

Description	Handheld transceiver
	Hariancia transceiver
Wireless communication	Access Technology (1.9 GHz)
Audio distortion	<1%
Integrated microphone	Uni-directional electret
Digital audio interface	USB-C 2-way digital audio interface
Battery power	3.7V Lithium polymer battery pack
Battery life	8 hours (fully charged)
Charging	2 contacts for cradle charging
Power	On/off button
Pairing	IR emitter to enable one-button pairing with amplifier
Dimensions (L x W x H)	6.0" x 1.1" x 1.1" (153 x 28 x 28mm)
Weight	2.6 oz (73g)



Cradle Charger

The two-slot microphone cradle charger can charge up to two Flexmikes or Sharemikes.

Description	Microphone cradle charger
Charging Slots	2 charging slots with magnetic interface
Power Input	5V/1.0A USB-C connector
Dimensions (W x H x D)	4.0" x 1.6" x 3.0" (102 x 41 x 76mm)



Media Connector

Integrate all classroom multimedia audio sources. Computers, DVD players, mobile devices, and more and be connected to the compact Media Connector which wirelessly transmits the signal to an Lightspeed audio system.

Description	Transceiver
Power Input	5V/1.0A USB-C connector
Wireless communication	Access Technology (1.9 GHz)
Tone control	1 bass / treble control
Digital audio interface	USB-C 2-way digital audio interface
Audio output	3.5mm stereo (x2) mixed with volume control
Audio Inputs	3.5mm stereo (x4) with volume control
Audio Link/pair indicator	1 LED on front panel
Device pairing	Push button
Dimensions (L x W x H)	7.75" x 4.25 x 1.25"(197 x 108 x 32mm)
Weight	7.36 oz (209g)